

Frequenzbereich	Frequency Range	<b>LMK / AM</b>	<b>UKW / FM</b>	<b>B III</b>	<b>L-Band</b>
Frequenz	Frequency	<b>0,15-16 MHz</b>	<b>87,5-108 MHz</b>	<b>174-240 MHz</b>	<b>1452-1492 MHz</b>
Impedanz	Impedance	<b>50 <math>\Omega</math></b>			
Anpassung	VSWR	<b><math>\leq 3,0 : 1</math></b>	<b><math>\leq 2,0 : 1</math></b>	<b><math>\leq 2,0 : 1</math></b>	<b><math>\leq 1,8 : 1</math></b>
Verstärkung	Amplification	<b>6 dB</b>	<b>14 dB</b>	<b>10 dB</b>	<b>0 dB</b>
Rauschmaß	Noise Figure		<b>3,5 dB typ.</b>	<b>2,0 dB typ.</b>	
Stromversorgung extern	Power Supply external	<b>+ 12 V, 25 mA</b>			
Stromversorgung	Power Supply	<b>+12 V, 25 mA</b>		<b>+12 V, 25 mA</b>	
Kabel RG 174	Cable RG 174	<b>145 mm</b>		<b>180 mm</b>	
Steckverbinder	Connector	<b>FAKRA (m)-B</b>		<b>FAKRA(m)-G</b>	